

2015 Iridium System Time Epoch Change

Iridium GO! devices will handle the time change automatically and do not require reprogramming.

Iridium 9555 and Iridium Extreme® customers can restore the correct time settings by following these steps:

1. Dial *#99#2014051114235500#
2. Press the green key
3. Turn off/on their phone

Iridium 9500, 9505 and 9505A customers will need to set the updated time and date from their phone menu.

The extended phone set-up menu must be set to "On" (see page 137 of Iridium 9505A user guide, page 149 of the Iridium 9500 user guide, or page 139 of the Iridium 9505 user guide), then follow these instructions to set time and date:

1. Follow the steps in "Getting to Phone Setup..." to get to Set Time and Date, and then press **OK** to select.
2. Press **MEMO** to choose Set Home Time + Date or Set Away Time + Date, and then press **OK**. You will see Enter Home Time or Enter Away Time and the time currently set.
3. Press **OK** to accept the displayed time.
or
Enter the time in 24-hour format, and then press **OK**. You will see Enter Home Date or Enter Away Time and the date currently set.
4. Press **OK** to accept the displayed date. You will see Completed.
or
Enter the date in day(dd)-month(mm)-year(yy) form and then press **OK**. You will see Completed.
5. Press and hold **C** to exit the menu.